

PS-CH01 Single Charger



- Storage/recharging for a single mobile
- Tabletop or wall mounting
- Built-in absent/present switch

These single chargers are designed for storing and charging a single DECT6000 or PS mobile. Each charger has a single storage unit contained in a heavy metal casing for tabletop use. The storage unit can be reversed in its metal casing so that the charger can be wall mounted.

Functions

Absent/Present switch

Each charger has a simple dip switch to choose between one of the following functions:

- · Absent the mobile in the charger is not available for calls while charging
- Present the mobile in the charger is available for calls while charging

Tabletop or wall mounting

The charger can be used as tabletop (when the storage unit is mounted vertically in the heavy metal base), or can be connected to the wall (when the storage unit is mounted horizontally in the base). Wall mounted chargers can be neatly positioned above and directly beside each other.

Power supply

FSD

The charger is supplied with a power adaptor (EU or UK version) for connecting to a 230 VAC supply.

Certifications and Approvals

CE marking acc. to Telecom directive 1999/5/EC

acc. to IEC/EN 60950-1 Safety EMC acc. to EN61000-6-1 acc. to EN61000-6-3 acc. to EN61000-4-2

contact: 8 kV air: 15 kV

acc. to IEC60068-2-29 acc. to IEC60068-2-6 Vibration

Parts Included

Quantity Component PS-CH01 Single Charger power adaptor (for EU or UK)

Technical Specifications

Electrical

Power supply in (adaptor) 230 VAC

Power supply out (adaptor) 9 VDC (max. ripple 100 mVpp)

Charging current 230 mA

Mechanical

Dimensions $(H \times W \times D)$ 52.5 x 71 x 58.2 mm

Weight (without adaptor): 370 g

Mounting tabletop or wall

Environmental

Operating temperature 10 °C to +35 °C

Relative humidity ≤95%

Ordering Information

PS-CH01-EU Single Charger (EU Adaptor) PS-CH01-EU

power adaptor with EU plug

PS-CH01-UK Single Charger (UK Adaptor) PS-CH01-UK

power adaptor with UK plug

atus B.V. www.atusbv.com